

## BPT Conversation Sheet

<u>Function</u>	<u>Terminals</u>
Microphone	1
Door Lock	2
Call Buzzer	3
Ground	4
Loudspeaker	5
Electronic Call	6

### Handsets

<u>BPT YC/251</u>	<u>1</u>	<u>2</u>	<u>3</u>	<u>4</u>	<u>5</u>	<u>6</u>
BPT C/251	1	2	3	4	5	6
BPT C/200	9	9	-	5	8	7
BPT E/200	2	2	-	1	3	4
BPT AZ/70	1	2	3	4	5	
BPT AZ/71	1	2	3	4	5	
BPT FD/50	1	2	3	4	5	
BPT FD/51	1	2	3	4	5	
LT603/N	1	T1	6	3	2	-
LT600WS	1	L	6	3	2	
Urmet	2	9	7	6-10-11	1	-
Elvox 870	2	7	6	3 - 4- 5	1	-
Tegui Horizon/N	4	3	1	2	5	-
Goldmar T/810G	5	C2	7	3	10	-
Goldmar T700	5	P1	com	3	10	0
Comelit Vox 2100	3	P1	1	4	2	-
Tesla 4fp/110/36/181	2	1	4	3	6	-
Fermax 2044 - 20440	2	1	-	3	6	4
STR	T	1	S	0	M	
STR HT 2003/2M	M	1	S	0	T	

**Handset Compatibility Chart for use with Golmar Universal Handsets  
T-710R & T-910R**

Handset	Lock	Mfc.	Comm	Speaker	Buzzer	Tone
Golmar T-710R	P1	5	3	10	7	0
Golmar T-910R	P1	5	3	10	7	0
Acet	5	10	2	7	9	
Auta	10	3	4	7	12	
Bpt	2	1	4	5	3	
BSTL	Z	R	O	T	I	
Centramatic	4	2	1	3	5	
Comelit	5	2	4	3	1	
Elvox	2	6	9	4	+	
Entryphone	3	P	B.F.G	L	A	
Farfisa	5	1	3	2	6	
Fermax TF-1Z	1	2	3	6	4	
Fermax TN-1 *	1	2	3	6		4
Fermax TN-Z	1	2	3	6	4	
Golmar M-500	4	5	3	10	7	
Golmar T-600	T	1	3	2	6	
Golmar T-800	P1	5	3	10		0
Golmar T-810	P1	5	3	10	7	
Golmar T-810R	P1	5	3	10	7	0
Golmar T-900	P1	5	3	10		0
Golmar T-910	P1	5	3	10	7	
Golmar T-1000	X	M	A	5	N	
Golmar T-1000A	11	5	3	10	12	
Golmar T-2800	4	5	3	10	7	
Golmar T-2802	4	5	3	10	7	
LT Terraneo	T1	1	3	2	6	
Selti	5	1	3	2	6	
Siedle	1	2	9/C	11	7	
STR NH200/205	I	M	O	T	S	
Techniphone	5	1	3	2	V	
Tegui GL	3	4	2	5	1	
Tegui Horizon Z	3	4	2	5	1	
Tegui Horizon E	3	4	2	5		1
Urmet	9	2	6	1		CA
Urmet	8/9	2	11	1	7	
Videx	5	1	3/7	2	6	

\* Fermax TN-1 Set JP1 jumper between 2 and 3. Do not change JP1 position for other models.

# Analogue / electronic audio intercom handset conversion sheet

Handset	Neg	Rec/ Speaker	Mic	Call	Lock
Sprint 600ws	3	1	2	6	L
BPT	4	5	1	3	2
Aiphone VC	1	2	3	B	4
Golmar	3	10	5	7	4
Urmet	6 6/10	2 2	1 1	7 CA	9 9
603/LT	3	1	2	6	T1
Vox2000	4	3	2	1	P1
STR	0	M	T	S	1
Sfera	1	4	3	5	6
Elvox	3	1	2	6	7
Comlit electronic Lolly pop style	C4	C3	C2	CS/5	P1